

Specifications



Eaton PV375

375W PowerVerter Ultra-Compact Car Inverter with 2 Outlets

General specifications

PRODUCT NAME	Eaton Tripp Lite series PowerVerter portable inverter
CATALOG NUMBER	PV375
UPC	037332119841
PRODUCT LENGTH/DEPTH	7.7 in
PRODUCT HEIGHT	2.5 in
PRODUCT WIDTH	5.8 in
PRODUCT WEIGHT	2.18 lb
COMPLIANCES	RoHS TAA Compliant
GLOBAL CATALOG	PV375

Product specifications

AUDIBLE ALARM	Dual function alarm indicates overload conditions or low DC input voltage of 10.5V or less.
CONTINUOUS OUTPUT CAPACITY (WATTS)	375
COOLING METHOD	Fan
CORD LENGTH DETAILS	3 ft. hardwire input cable, 16 gauge, 2 wire
DC SYSTEM VOLTAGE (VDC)	
INPUT CONNECTION TYPE	12V DC cigarette lighter input plug connection
AMPERAGE RATING PER WATT	Full continuous load - 40A at 12V DC, No load - 0.65A at 12V DC
OUTPUT FREQUENCY REGULATION	60 Hz (+/- 3 Hz)
OUTPUT VOLTAGE REGULATION	Maintains PWM sine wave output voltage of 115 V AC (+/- 8 VAC)
OVERLOAD PROTECTION	40A automotive input fuse
PEAK OUTPUT CAPACITY (WATTS)	600
POWER CORD JACKET TYPE	SJT
FREQUENCY COMPATABILITY	60 Hz
RELATIVE HUMIDITY	0-95% non-condensing
SWITCHES	Lighted on/off power switch
VOLTAGE COMPATIBILITY (VDC)	12
MATERIAL	Aluminum, Steel
OUTPUT RECEPTACLES	5-15R
PACKAGE CONTENTS	Warranty information PV375 Inverter Instruction manual
PRODUCT FEATURES	12V DC cigarette lighter input plug connection
NOMINAL OUTPUT VOLTAGE	120V

Resources

BROCHURES	Laptop/Tablet Accessories Brochure (English)
	Solutions for Utility Service/Work Trucks and Cargo Delivery Service Vans
	Tripp Lite 120V Inverter/Chargers Brochure (English)
MANUALS AND USER GUIDES	Owner's Manual for PowerVerter Inverters
TECHNICAL DATA SHEETS	How to Use the Equilization Function (English)

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

